

IPLED-48x48-RGB-6.67-ODX

(Indoor or Outdoor Exposed)





displays

Pictures shown are of 10mm Pitch Displays.

Available in <u>6.67 mm</u>, these displays can be seen from hundreds of feet away. <u>6.67 mm</u> models offer more pixels allowing for greater detail. Indoor or outdoor they can be used for multiple purposes: as an information sign, a status sign with real time data or any other need. Thousands of full color bitmaps can be stored on the internal micro SD card. This sign has the same connectivity as our previous model signs and is offered at a lower cost. It is serviceable from the front with a powder coated aluminum case and is substantially lighter in weight.

>Specifications

Length: 12.6"(320mm) Height: 12.6"(320mm)

Depth: 4"(101.6mm)

• Power Requirements

Power Consumption:

Weight: 5.5 lbs est. (2.49 kg).

Input - 95 ~ 260VAC at 50 ~ 60Hz

or 12 - 24 DC*

135W maximum

27W Typical

Mechanicals

6.67

Internals

6.67 MM Pitch LEDs: Array 48x48 2304 pixels; full Color, R/G/B Processor: ARM A8 at 1GHz; Memory: 1GB SDRAM; uSD Memory card: 8GB Min.

• Electrical

Ethernet - RJ45 - 10/100Mb Cat5. USB 2.0 - Host - Type A connector. Audio - 3.5mm Stereo Jack - 3 conductor. Case: 1" Knockout opening. Power Input: Conduit Cutout. Wago Lever Nuts

Environmental

Operating Temperature: -34°C ~65°C ambient. -30°F ~ 150°F ambient. Relative Humidity: up to 90 % non-condensing. Ethernet Isolation: 1500VAC min per IEEE 802.3. Enclosure: PTFE gasketed. Weather-sealed enclosure.

* DC Power Supply sold separately.





Remote 'snapshot'

Not where you can see your display, no problem. View exactly what is on the display no matter where you are. The sign generates an instant copy of what is being displayed and sends it right to your browser.

Integrated 10/100 Ethernet

This is the core of our technology which allows for superior ease of use and integration in conjunction with the unit's built in web-server. TCPIP enabled out of the box. Use built-in support for DHCP and NTP to aid in your ease of configura tion.

Value Colo		Richt	Source	
75 affi	100	No		×
100 400	000	No		
	TSorterGet			0
		1		
	TSorterion 15	1		2
				*
	15	1		*

Data thresholds

Set thresholds on your data to change your message color or state to bring impact to an event.

• Server-free solution

With easy web-based interfaces and easy to program XML data structures, no longer do you need middleware or any additional hardware to accumulate data saving you time, money and resources.

>Display Features



*Direct PLC Interfaces

Connect to Standard based PLC's including: Ethernet/IP[™], Modbus/TCP, Melsec(Mistubishi), FINS (OMRON), and OPC.

• Browser based interface

Ease of use exemplified. Manage your display from a simple web-browser anywhere - any time. Send messages, check status, and manage thresholds, layouts, remote or local data fields all from web pages hosted on the sign. No software to install and no custom programming needed.

Live message elements

Insert data into any message. You can have real-time data and see it update dynamically on the display. Any message may contain static or scrolling text, live data, database elements, clocks, bit-mapped graphics or any combination therein.

Titan1 Orientaria (1991 x 1080 Orienta	AnyPLC Dimensional 1909 (1080) Debic 15
Target 10 551	Targer (D) 503
topmiddlebottom Onercos: 1900 + 1980 Draw 72	
New blank layout	New grid layout Crass a new lyoct that contains a fixed number of rows and solutions

• Dynamic sign layouts

Schedule any number of layouts with our Playlist manager. Show real-time data, statistics, company news, safety informa tion, or general messages in their own unique layout to get the impact you want. The Playlist manager allows you to schedule the times and order - it is all under your control.





• Fonts, graphics and effects

Use any of the 44 built-in text or graphics fonts to build your message. Add pizazz using the built-in entry and exit effects.

	Then	Otherwise		
I	Enable a layout Atematication	Enable a layout Cruck taket Garage		
	Action sequence 1	Action sequence 1		
	Disable a layout Church Street Garage	Disable a layout		
	Action sequence 2	Action sequence 2		

• Conditions/Program Logic

Program logic can be tied to variables on the sign. As data is changed "Program logic" can be used to Activate/Deactivate Messsages, Layouts, Thresolds, Commands or even update other variables on the sign.

Simple Integration/Open Interface

Use simple standard XML syntax and constructs to send data to the display. No proprietary protocols, syntaxes, or languages to learn. Any XML capable application like MS Excel or SQL Server or programming language like Perl, VB, or C# can easily update data fields or elements on the sign.



www.ipdisplavs.com